

Errata

- Releasing Reset Condition without Clock
- Clearing Lock-bits at High V_{CC} or Temperature
- Wrong Clearing of XTRF in MCUSR
- Reset during EEPROM Write
- Serial Programming at Voltages below 3.0 Volts

5. Releasing Reset Condition without Clock

If an external reset or a watchdog reset occurs while the clock is stopped and the reset is released before the clock is restarted, the internal reset will time-out after the start-up delay, which is independent of the external clock. If no external clock pulses are present in the period when internal reset is active, the reset does correctly causes tri-stating of the I/O while the reset is held. However, if the internal reset is released before the clock starts running, the part does not clear its I/O registers, nor set PC to 0x00. Here, stopping the clock refers to gating the external clock input. Power-down mode does not have this issue.

Problem Fix/Workaround

Make sure the clock is running whenever an external reset can be expected. If the Watchdog is used, never stop an external clock.

4. Clearing Lock-bits at High V_{CC} or Temperature

If the temperature is too high, and/or the programming voltage is too high, the clearing of lock-bits might fail.

Problem Fix/Workaround

Keep V_{CC} below 5.0 volts at room temperature when performing a chip erase.

3. Wrong Clearing of XTRF in MCUSR

The XTRF flag in MCUSR will be cleared when clearing the PORF flag. The flag does not get cleared by writing a "0" to it.

Problem Fix/Workaround

Finish the test of both flags before clearing any of them. Clear both flags simultaneously by writing "0" to both PORF and XTRF in MCUCR.

2. Reset during EEPROM Write

If reset is activated during EEPROM write, the result is not what should be expected. The EEPROM write cycle completes as normal, but the address registers are reset to "0". The result is that both the address written and address 0 in the EEPROM can be corrupted.

Problem Fix/Workaround

Avoid using address 0 for storage unless you can guarantee that you will not get a reset during EEPROM write.

1. Serial Programming at Voltage below 3.0 Volts

At voltages below 3.0 volts, serial programming might fail.

Problem Fix/Workaround

Keep V_{CC} at 3.0 volts or higher during In-System Programming.



8-bit **AVR**[®]
Microcontroller
with 2K Bytes of
In-System
Programmable
Flash

AT90S/LS2323
Rev. G
Errata Sheet





Atmel Headquarters

Corporate Headquarters
2325 Orchard Parkway
San Jose, CA 95131
TEL (408) 441-0311
FAX (408) 487-2600

Europe

Atmel SarL
Route des Arsenaux 41
Casa Postale 80
CH-1705 Fribourg
Switzerland
TEL (41) 26-426-5555
FAX (41) 26-426-5500

Asia

Atmel Asia, Ltd.
Room 1219
Chinachem Golden Plaza
77 Mody Road Tsimhatsui
East Kowloon
Hong Kong
TEL (852) 2721-9778
FAX (852) 2722-1369

Japan

Atmel Japan K.K.
9F, Tonetsu Shinkawa Bldg.
1-24-8 Shinkawa
Chuo-ku, Tokyo 104-0033
Japan
TEL (81) 3-3523-3551
FAX (81) 3-3523-7581

Atmel Product Operations

Atmel Colorado Springs

1150 E. Cheyenne Mtn. Blvd.
Colorado Springs, CO 80906
TEL (719) 576-3300
FAX (719) 540-1759

Atmel Grenoble

Avenue de Rochepleine
BP 123
38521 Saint-Egreve Cedex, France
TEL (33) 4-7658-3000
FAX (33) 4-7658-3480

Atmel Heilbronn

Theresienstrasse 2
POB 3535
D-74025 Heilbronn, Germany
TEL (49) 71 31 67 25 94
FAX (49) 71 31 67 24 23

Atmel Nantes

La Chantrerie
BP 70602
44306 Nantes Cedex 3, France
TEL (33) 0 2 40 18 18 18
FAX (33) 0 2 40 18 19 60

Atmel Rousset

Zone Industrielle
13106 Rousset Cedex, France
TEL (33) 4-4253-6000
FAX (33) 4-4253-6001

Atmel Smart Card ICs

Scottish Enterprise Technology Park
East Kilbride, Scotland G75 0QR
TEL (44) 1355-357-000
FAX (44) 1355-242-743

e-mail

literature@atmel.com

Web Site

<http://www.atmel.com>

BBS

1-(408) 436-4309

© Atmel Corporation 2001.

Atmel Corporation makes no warranty for the use of its products, other than those expressly contained in the Company's standard warranty which is detailed in Atmel's Terms and Conditions located on the Company's web site. The Company assumes no responsibility for any errors which may appear in this document, reserves the right to change devices or specifications detailed herein at any time without notice, and does not make any commitment to update the information contained herein. No licenses to patents or other intellectual property of Atmel are granted by the Company in connection with the sale of Atmel products, expressly or by implication. Atmel's products are not authorized for use as critical components in life support devices or systems.

ATMEL® and AVR® are the registered trademarks of Atmel.

Other terms and product names may be the trademarks of others.



Printed on recycled paper.